



AREX SOLAR FLOODLIGHT LED BLACK MULTI FUNCTION - AR-SFL(R)-10W

Products Information:

Arex Solar Wall Light LED comes into three different modes:

MODE A: Constant Lighting Mode (Lamp not connected with solar panel)
Under this mode, the PIR sensor & Photo cell control will not work.

Mode A1: Press ON OFF Button 1st time, it turns on to 30% constant brightness.



Mode A2: Press ON/OFF Button 2nd time, it turns on to 100% constant brightness.



Mode A3: Press ON/OFF button 3rd time, it turns off

MODE B: Sensor Mode (Lamp connected with solar panel)
Under this Mode, the lamp will automatically light on at night, and light off during day time.

Mode B1 : Press ON/OFF 1st time, automatically turns on to 100% brightness (1100lm) when motion is detected in range ≤6m and then turns to 5% brightness in 20 seconds if no motion.



Mode B2: Press ON/OFF 2nd time, it turns automatically turns on and remains 100% brightness (1100lm) for 5hours. After 5hours or when battery capacity is less than 30%, it turns to Mode B1.



Mode B3: Press ON/OFF 3rd time, it turns OFF

Products Features:


- Wall mounted
- Standable
- Foldable
- Hangable
- Portable
- Powerbank

Application Area:

- House, garden, entrance, pathway
- Others

ADDITIONAL POWERBANK FUNCTION:

Indicator of Battery
Capacity: 25%, 50%,
75%, 100%



USB Output: 5.0V/1.0A
DC-Micro Input:
5.0V/1.0A

PRODUCTS SPECIFICATIONS

Model:	AR-SFL (R)-10W	Product Code:	1023000021 1023000022
Wattage (W):	10W	Led Quantity:	55 pcs
Input Voltage (V):	2.8V – 4.2V	Rated Lumen:	1,100 lm
Working currents(A):	7200mA	Lumen Efficiency:	106lm/w
CCT:	3000K 6500K	Beam Angle:	120°
CRI:	≥80	Rated Life(L70):	35,000 Hours
Light Source:	SMD 2835	Barcode:	9555106310115 9555106310122
Operating Environment:	From -15°C to +55°C		